

# NTV44

## По вопросам продаж и поддержки обращайтесь:

Алматы (7273)495-231  
Архангельск (8182)63-90-72  
Астрахань (8512)99-46-04  
Барнаул (3852)73-04-60  
Белгород (4722)40-23-64  
Брянск (4832)59-03-52  
Владивосток (423)249-28-31  
Волгоград (844)278-03-48  
Вологда (8172)26-41-59  
Воронеж (473)204-51-73  
Екатеринбург (343)384-55-89  
Иваново (4932)77-34-06  
Ижевск (3412)26-03-58  
Иркутск (395)279-98-46  
Россия (495)268-04-70

Казань (843)206-01-48  
Калининград (4012)72-03-81  
Калуга (4842)92-23-67  
Кемерово (3842)65-04-62  
Киров (8332)68-02-04  
Краснодар (861)203-40-90  
Красноярск (391)204-63-61  
Курск (4712)77-13-04  
Липецк (4742)52-20-81  
Магнитогорск (3519)55-03-13  
Москва (495)268-04-70  
Мурманск (8152)59-64-93  
Набережные Челны (8552)20-53-41  
Нижний Новгород (831)429-08-12  
Киргизия (996)312-96-26-47

Новокузнецк (3843)20-46-81  
Новосибирск (383)227-86-73  
Омск (3812)21-46-40  
Орел (4862)44-53-42  
Оренбург (3532)37-68-04  
Пенза (8412)22-31-16  
Пермь (342)205-81-47  
Ростов-на-Дону (863)308-18-15  
Рязань (4912)46-61-64  
Самара (846)206-03-16  
Санкт-Петербург (812)309-46-40  
Саратов (845)249-38-78  
Севастополь (8692)22-31-93  
Симферополь (3652)67-13-56  
Казахстан (7172)727-132

Смоленск (4812)29-41-54  
Сочи (862)225-72-31  
Ставрополь (8652)20-65-13  
Сургут (3462)77-98-35  
Тверь (4822)63-31-35  
Томск (3822)98-41-53  
Тула (4872)74-02-29  
Тюмень (3452)66-21-18  
Ульяновск (8422)24-23-59  
Уфа (347)229-48-12  
Хабаровск (4212)92-98-04  
Челябинск (351)202-03-61  
Череповец (8202)49-02-64  
Ярославль (4852)69-52-93

# NTV 44 SINGLE



## **FUNCTION:**

The NTV 44 Processing power pack was specially developed for the use of the L-probe on conventional controls. A microprocessor converts the incoming L-probe signal into an equivalent mV signal from an oxygen probe. The required correction factors K1, K2 are entered using the T300 terminal. A two-point comparison can also be carried out. Additional functions such as probe rinsing, recovery time, and rinsing interval can also be entered via the new T300. The NTV 44 Processing supplies highly constant voltages (e.g. to lambda probes and other consumers). An active four-wire circuit ensures that line resistances up to 1 ohm and the associated voltage drops are compensated.

In order to avoid oxidation effects on the lambda probe heating, which shortens the life of the probe, the polarity of the heating voltage can optionally be switched automatically at regular time intervals.

## TECHNICAL SPECIFICATIONS:

<b>Design:</b>	Housing made of Makralon for wall mounting
<b>Dimensions:</b>	185 x 120 x 90 mm (LxWxH)
<b>Connection:</b>	Plug-in screw terminals wire cross-section max. 2.5 mm
<b>Connection for L-probe:</b>	1 m cable with plug and coupling
<b>Cable feeds:</b>	Three PG 9 screw connections
<b>Auxiliary voltage:</b>	115 or 230 Vac $\pm$ 10% / 50-60 Hz, max. 50 VA
<b>Input measuring probe:</b>	0 ... 1300 mVdc (L probe signal)
<b>Output probe:</b>	0 ... 1300 mVdc (L-probe signal, 1: 1) Option: current output galvanically isolated 0 ... 20 mA or 4 ... 20 mA
<b>Output power pack:</b>	12.00 Vdc, max. 3 A, Tol. $\pm$ 20 mV (heating voltage for L-probe)
<b>Permissible line resistance:</b>	Max. 1 ohm
<b>Climate:</b>	Storage: -10 ... + 70 ° C Operation: 0 ... + 50 ° C 5 ... 95% rel. Moisture, free of condensation

**По вопросам продаж и поддержки обращайтесь:**

Алматы (7273)495-231	Казань (843)206-01-48	Новокузнецк (3843)20-46-81	Смоленск (4812)29-41-54
Архангельск (8182)63-90-72	Калининград (4012)72-03-81	Новосибирск (383)227-86-73	Сочи (862)225-72-31
Астрахань (8512)99-46-04	Калуга (4842)92-23-67	Омск (3812)21-46-40	Ставрополь (8652)20-65-13
Барнаул (3852)73-04-60	Кемерово (3842)65-04-62	Орел (4862)44-53-42	Сургут (3462)77-98-35
Белгород (4722)40-23-64	Киров (8332)68-02-04	Оренбург (3532)37-68-04	Тверь (4822)63-31-35
Брянск (4832)59-03-52	Краснодар (861)203-40-90	Пенза (8412)22-31-16	Томск (3822)98-41-53
Владивосток (423)249-28-31	Красноярск (391)204-63-61	Пермь (342)205-81-47	Тула (4872)74-02-29
Волгоград (844)278-03-48	Курск (4712)77-13-04	Ростов-на-Дону (863)308-18-15	Тюмень (3452)66-21-18
Вологда (8172)26-41-59	Липецк (4742)52-20-81	Рязань (4912)46-61-64	Ульяновск (8422)24-23-59
Воронеж (473)204-51-73	Магнитогорск (3519)55-03-13	Самара (846)206-03-16	Уфа (347)229-48-12
Екатеринбург (343)384-55-89	Москва (495)268-04-70	Санкт-Петербург (812)309-46-40	Хабаровск (4212)92-98-04
Иваново (4932)77-34-06	Мурманск (8152)59-64-93	Саратов (845)249-38-78	Челябинск (351)202-03-61
Ижевск (3412)26-03-58	Набережные Челны (8552)20-53-41	Севастополь (8692)22-31-93	Череповец (8202)49-02-64
Иркутск (395)279-98-46	Нижний Новгород (831)429-08-12	Симферополь (3652)67-13-56	Ярославль (4852)69-52-93
Россия (495)268-04-70	Киргизия (996)312-96-26-47	Казахстан (7172)727-132	